

## Terminal for fitting crimping terminal

## PB series (1000pcs/pack)

- This crimping terminal is used for supplying power supply line to a mother board, etc.
- Use of this product is limited to through hole boards.
- Please set the land diameter of  $\phi$  7 or over for PB-1 and PB-2, and  $\phi$  8 or over for PB-3 and PB-4. Also, please ensure that the solder is lifted to the part face. (Tightening torque: 6kgf-cm or less)
- Material: Brass
- Finish G:Gold plating over nickel base
  S:Tin plating over nickel base
- Rated current: 30A










Part No.	Plating	А	L	С	D	Е	M(Tap)	Printed board fitting hole	Printed board land diameter	Printed board thickness
PB-1-G	Gold	6	6	3.3	2.02	3.5	М3	φ 2.0 to φ 2.1	φ 7	1.6, 2.0
PB-1-S	Tin	6	6	3.3	2.02	3.5	М3	φ 2.0 to φ 2.1	φ7	1.6, 2.0
PB-2-G	Gold	6	6.5	5	3.02	3.5	М3	φ 3.0 to φ 3.1	φ7	3.2
PB-2-S	Tin	6	6.5	5	3.02	3.5	M3	φ 3.0 to φ 3.1	φ7	3.2
PB-3-G	Gold	7	8	3.3	3.02	5	M4	φ 3.0 to φ 3.1	φ8	1.6, 2.0
PB-3-S	Tin	7	8	3.3	3.02	5	M4	φ 3.0 to φ 3.1	φ8	1.6, 2.0
PB-4-G	Gold	7	8	5	3.02	5	M4	φ 3.0 to φ 3.1	φ8	3.2
PB-4-S	Tin	7	8	5	3.02	5	M4	φ 3.0 to φ 3.1	φ8	3.2


■ Please use □PB series for the type with different height.


## Small terminal for electric wire installation

## MM series (100pcs/pack)


- This is used for fitting or removing a thin wire to a PC board.
- When fitting a small number of wires to a PC board, this product can be fit to any place and this makes pattern design very easy.
- Material: Brass
- Finish: Gold plating over nickel base
- Rated current: MM-1-1:10A
  - : MM-2-1:20A
- Screw: M1.0 pan head © nickel plating (MM-1-1)
  - : M1.7 pan head ⊕ nickel plating (MM-2-1)
- Printed board fitting hole diameter: φ 1.0 (MM-1-1)
  - $: \phi \ 1.6 (MM-2-1)$
- Diameter of electric wire that can be fit: φ 0.8 or less (MM-1-1)
  - $: \phi \ 1.5 \text{ or less (MM-2-1)}$
- Screw is included.











Part No.: MM-2-1